

| Features | | |
|--|------|------|
| | 390 | 391 |
| 200A AC Current measurement | * | * |
| Digital display counts | 6000 | 6000 |
| Display type(Negativity display) | * | * |
| Compact size | * | * |
| Data Hold & MAX/MIN Function | * | * |
| Peak Value & Inrush Current | | * |
| Backlight for button, knob Switch & Flashlight | * | * |
| Low battery indication | * | * |
| 17mm Jaw opening | * | * |
| Auto sense Voltage | * | * |
| NCV | * | * |
| Low Z & True RMS | * | * |
| Non contact voltage test | | * |

| Specifications | | | | |
|--------------------------|------------------------------|-----------------|--------------|-----|
| Function | Max Range | Basic Accuracy | 390 | 391 |
| $\pm(0.8\%+3d)$ | 1000V | $\pm(0.8\%+3d)$ | * | * |
| Voltage AC | 1000V | $\pm(1.0\%+3d)$ | * | * |
| Current AC | 200A | $\pm(3.5\%+5d)$ | * | * |
| Resistance | 60M Ω | $\pm(3.0\%+5d)$ | * | * |
| Capacitance | 6000mF | $\pm(2.5\%+5d)$ | * | * |
| Non contact voltage test | 600V | $\pm(2.5\%+5d)$ | | * |
| LoZ (< 600V) | | | ~3K Ω | |
| Continuity check | Buzzer sounds at 50 Ω | | | |
| Diode test Test | current 0.35mA 3V | | | |